

## Power Box DS Sources

Universal linear power supply for up to 5 components & 1 turntable

- Purest & cleanest power using non-switching power supply
- 5 Box Design component & 1 turntable power output
- Not suitable for integrated & power amplifiers, receivers etc
- Soft start system avoids current inrush in primary winding
- Audio type toroidal transformer
- Main isolating transformer with copper foil shielding
- Secondary voltage rectification with precise regulation
- High filtration capacity (10.000  $\mu$ F)
- Low ESR capacitors
- Low noise components with surge protection
- Available in silver or black

### Technical data

Input voltage	AC 230V/50Hz IEC C15 connector (120V/60Hz US)
Output voltage / current	2 x 9V / 2A max (1,3mm connector) 3 x 18V / 1A max (2,5mm connector) (see compatibility chart on page 2) 1 x 15V / DC-turntable (2,1mm connector) (all of Pro-Ject DC-powered turntables)
CAUTION: Do not use for power amps, integrated amp, receivers & other voltages!	
Filtration capacity	10.000 $\mu$ F
Output voltage ripple	< 1mV
Dimensions W x H x D	203 x 72 x 207mm
Weight	3.200g



### Power Box DS Sources: Cleanest power for ultimate sound of Box Design components plus turntable!

It is a proven fact that a power supply is a very important part of the audio path and significantly contributes to the sonic quality of an audio product. In order to offer the possibility of improving sound quality, we designed our linear power supply Power Box DS Sources. It significantly enhances the sound quality of up to six Box Design components, like streamers, CD players, pre-amplifiers and also offers the possibility to connect a DC-driven turntable.

A linear power supply consists of a massive toroidal transformer with shielding between primary and secondary winding, which acts as an isolating transformer and avoids penetration of interferences from mains into the audio component. The built-in transformer has a much higher power reserve compared to the standard power adapter. It has very low output impedance and in combination with large filtration capability it can easily manage all power needs. Sound staging, darkness of silent backgrounds and small detail resolution will improve strongly and contribute to a far better overall performance of each component.

Six standard connection cables are included in delivery. Special highend super shielded connection cables in these lengths are available on request: 20cm, 40cm, 80cm, 1m.



**All Power Box outputs are DC only, do not connect AC equipment!**  
**If in doubt, consult your dealer!**

	<b>DC only</b>	Power Box DS Amp	Power Box DS Sources	Power Box MaiA DS	Power Box MaiA
A/D Phono Box S	18V/500mA		•	•	•
Amp Box DS	2x48V	•			
Amp Box mono DS	2x48V	•			
Amp Box S	20V/3A				•
Amp Box S mono	24V/5A				•
Bluetooth Box E	9V/300mA		•	•	•
Bluetooth Box S	9V/300mA		•	•	•
CD Box DC	9V/2A		•	•	•
CD Box DS	18V/1A		•	•	•
CD Box S	9V/2A		•	•	•
DAC Box DS	18V/500mA		•	•	•
DAC Box E	18V/500mA		•	•	•
DAC Box S FL	9V/300mA		•	•	•
DAC Box S USB	9V/300mA		•	•	•
Dock Box S Digital	9V/2A		•	•	•
Dock Box S Fi	9V/2A		•	•	•
Head Box DS	18V/500mA		•	•	•
Head Box S	18V/500mA		•	•	•
Head Box S USB	18V/500mA		•	•	•
MaiA	20V/3A				•
MaiA preamplifier	18V/1A		•	•	•
MaiA CD	9V/2A		•	•	•
MaiA DS	20V/3A			•	
Media Box S	9V/2A		•	•	•
Phono Box DS	18V/500mA		•	•	•
Phono Box DS+	18V/500mA		•	•	•
Phono Box E	18V/500mA		•	•	•
Phono Box	18V/500mA		•	•	•
Phono Box MM	18V/500mA		•	•	•
Phono Box S	18V/500mA		•	•	•
Phono Box USB	18V/500mA		•	•	•
Phono Box USB V	18V/500mA		•	•	•
Pre Box S	18V/500mA		•	•	•
Pre Box DS	18V/500mA		•	•	•
Receiver Box S	20V/3A				•
Record Box E	18V/500mA		•	•	•
Remote Box S	9V/2A*		•	•	•
Speed Box DS Strobo	18V/1A		•	•	•
Speed Box DS	18V/1A		•	•	•
Speed Box S 50Hz	18V/500mA		•	•	•
Speed Box S 60Hz	18V/500mA		•	•	•
Stereo Box DS	24V/5A			•	
Stereo Box S	20V/3A				•
Stereo Box S Phono	20V/3A			•	•
Stream Box DS net	9V/2A		•	•	•
Stream Box DS+	18V/1A		•	•	•
Stream Box DSA	24V/5A			•	
Tube Box DS	18V/1A		•	•	•
Tube Box S	18V/1A		•	•	•

Explanation: components marked with a dot are compatible with type of Power Box listed above!