

CD PLAYER

CD14



Wolfson premium
24-bit/192kHz Digital
to Analogue Converter



iOS / Android
control App*



Supports MP3
playback



Includes remote
control



12 volt trigger
input

In 1989, Rotel confirmed its digital audio expertise with the launch of the RCD-855 CD player. The press was overwhelming in its praise, one critic going so far as to call it “The steal of the century”, and since then Rotel has never looked back. The CD14 design begins with a carefully engineered power supply

to ensure separate, ripple-free voltage and current to both digital and analogue circuits. It maintains the same clean lines and intuitive operation as the other 14 series models, while demonstrating an uncanny ability to resolve even the smallest musical details in a recording.

Get the most out
of your CD collection
with Rotel's compact
disc players.
See more at

rotel.com



*requires connection to A14 or T14

CD PLAYER

CD14



SPECIFICATIONS

Total Harmonic Distortion + Noise	0.002% @ 1kHz
Intermodulation Distortion	0.002% @ 1kHz
Frequency Response (± 0.5 db)	20-20,000Hz
Channel Balance	± 0.5 db
Phase Linearity	± 0.5 degree
Channel Separation	> 115 dB @ 10 kHz
Signal to Noise Ratio ("A" weighting)	> 118 dB
Dynamic Range	> 99 dB
Digital to Analog Converters	Wolfson 24 bit/192kHz DAC
Analog Output Impedance	100 Ohms
Digital Output	0.5 Volt, Peak to Peak
Load Impedance	75 Ohms

General	
Power Requirements (AC)	
Europe	230V, 50Hz
USA	120V, 60Hz
Power Consumption	15 watts
Standby Power Consumption	< 0.5 watts
Finishes	Silver and Black
Dimensions (W x H x D)	430 x 93 x 31.2mm 17" x 3 5/8" x 12 5/16"
Front Panel Height	80mm, 3 1/8"
Weight (net)	5.9kg, 13 lb

Get the most out of your CD collection with Rotel's compact disc players. See more at

rotel.com

