

Speed Box DS

Electronic motor control and speed change

- Quartz-generated high precision electronic speed regulation with microprocessor control
- Sound improvement through motor running smoothness
- Clean power decoupled from mains interference
- Allows electronic speed change 33 & 45 rpm
- 78 rpm possible with optional accessory pulley
- Suitable for all turntables with 16 volt or 230 volt AC motor, up to 3 watts max. power consumption
- Metal case shields electronics from vibration and electromagnetic interference
- Small size allows installation close to record player
- Outboard power supply included
- Available in silver or black finish

OUTPUT	230V AC 13mA & 16 V AC 190mA (up to 3W max) 40cm cable supplied
SPEED STABILITY	+/- 0,001%
POWER SUPPLY	18V/1000mA DC (100-240 volts primary)
DIMENSIONS	103 x 72 x 104 mm (WxHxD)
WEIGHT	1360 g without power supply

Use only with 230 & 16 volt power connection, that use AC motors

Does not work with DC power supplied turntables

Follow information on www.project-audio.com

For turntables not listed on homepage, consult your dealer!



Retail price
399,00 €

Upgrade to best possible turntable performance with convenient speed changeover through keypress!

A very useful accessory for many Pro-Ject turntables, that do not offer a built-in electronic speed change. The Speed Box DS performs this change by the push of a button between 33 and 45 rpm! The quartz regulation and filter circuit gives a far better speed stability for smooth and undisturbed motor operation. Speed Box DS is compatible with a lot of Pro-Ject turntables (see list on homepage) and some also offer the possibility to play 78 rpm records with the addition of a special accessory pulley!



< Version in black

Rear view >

- ◇ DC in (18V)
- ◇ AC out (16V & 230V)

