

Stereo Box S Phono

Stereo integrated amplifier with phono input

- 2x 37 watts @ 4 ohms
- 2 ohms drive capability
- Low noise pure analogue audio circuitry
- Dual mono design principle
- 3 stereo line & 1 phono input (RCA)
- MM capability
- Fixed line level record output
- Variable line level output
- Motor drive potentiometer
- IR remote included
- High class metal casing

Technical data

Power output	2x 25W / 30W at 8 / 4 ohms
Frequency response	20Hz - 20kHz (+0dB, -0,5dB)
Stereo inputs	3 pair RCA/Cinch sockets stereo line 1 pair phono MM input (RCA)
Signal-to-noise ratio	> -100dBA
RIAA equalisation accuracy	20Hz - 20kHz (+/-0,5dB)
Stereo outputs	Stereo RCA (variable level) 3,5mm jack (fixed level)
Speaker connectors	4mm Ø banana plugs, spades connectors or naked wire
Power supply	20V/3A DC; 100 - 240V, 50/60Hz
Standby Power consumption	< 1 watt
Dimensions W x H x D	206 x 36 x 150 (153mm with sockets)
Weight	1750 g without power supply



Retail price
359,00 €

Stereo Box S: stylish integrated amplifier with phono & line inputs

This small audiophile integrated amplifier strictly follows our less is more principle in a pure analogue circuitry. Therefore it offers „strictly analogue“ line level inputs and a high-quality phono preamp. If digital input options are needed, just add one of our DAC Box components and you will get analogue and digital input options and best possible audio reproduction!

4 stereo line level inputs (RCA) and a built-in phono input guarantee lifelike performance out of a stylish amplifier. Stereo Box S Phono offers low noise and solid output power for audiophile playback at surprisingly low cost. An IR remote comes with the unit and makes usage a piece of a cake. The massive metal casing is elegant and effectively protects against interferences. Stereo Box S Phono is available in silver or black.

